



Changing the Commander Hi Path 2000, 3500, 3550, 3700 & 3800 Time and Date

To Set Time and Date:

Programming to be done on main station (port 101 or 102)

Dial	*95	
Dial user	23646	Press ✓
Enter password	23646	Press ✓
Dial (time)	12	Press ✓
Enter time (hh:mm)24hours	1645	Press ✓
Press	⇒	Press ✓ + ✓
Enter Date (231003)	231003	Press ✓
Press	Service Key	Exit programming