



Changing the Commander Connect Time and Date

To Set the Time and Date:

- When entering into programming mode do not lift the receiver
- From the Programming Station press the  Programming Key
- Press the Scroll Down Key () until **System Programming** is displayed
- Select **System Programming** (using grey menu key next to display)
- Enter the System Programming Password – 1111. If System Programming Password fails and display shows **Invalid** on display contact CCO for assistance **1300 13 88 99**.
- Select **System** (using grey menu key next to display)
- Select **Time and Date** (using grey menu key next to display)
- Enter the correct time in 24-hour format, (e.g. 1:30pm as 1330). The display will prompt for date to be entered
- Enter in the correct date in DDMMYY format, (e.g. 1 January 2001, 010101) The display will now revert back to programming menu.
- Press **[HANDSFREE]** key to finish programming.
- Note: Following a system reset, the time shown will be 12:00 with the date 01-01-99.
- In the event of a power failure, you will need to reset the time and date.
- Text in a **BOX** indicates relevant area from keystation display Please refer to page 54 in the Commander Connect Owners Handbook for information.